



Product Information

Stand adapter

19400



Weight: 0.4kg (0.9lbs)

Load capacity: Max. 5.0kg (11.0lbs)

Dimensions (W x D x H): 100 x 79 x 79 mm (3.94" x 3.11" x 3.11")

Adjustment range: Inclination -45° to 45°

Clamp bracket

19410



Weight: 0.76kg (1.7lbs)

Load capacity: Max. 4.0kg (8.8lbs)

Dimensions (W x D x H): 100 x 100 x 400 mm (3.94" x 3.94" x 15.75")

Height adjustment: 240 mm (9.45")

Clamping range: 10-51 mm (0.39"-2.01") plate, Tube with 15-51 mm (0.59"-2.01") diameter

Ceiling bracket

19420



Weight: 2.2 kg (4.9 lbs) Load capacity: Max. 28.0 kg (61.7 lbs) Dimensions (W x D x H): 126 x 160 x 180 mm(4.96" x 6.30" x 7.09")

Adjustment range: Tilt 0° to 75°

Wall bracket

19430



Weight: 2.3 kg (5.1 lbs)

Load capacity: Max. 22.0 kg (48.5 lbs)

Dimensions (W x D x H):

126 x 305 x 205 mm (4.96" x 12.01" x 8.07") Adjustment range: Tilt -45° to 45° / Pan 360° Wall / Ceiling bracket

19440



Weight: 1.1 kg (2.4 lbs)

Load capacity: Max. 6.0 kg (13.2 lbs)

Dimensions (W x D x H):

95 x 220 x 170 mm (3.74" x 8.66" x 6.69") Adjustment range: Tilt -45° to 45° / Pan 360°













| Bracket type | Stand adapter | Clamp bracket | Ceiling bracket | Wall bracket | Wall / Ceiling bracket |
|------------------------|---------------|---------------|-----------------|--------------|------------------------|
| | 19400 | 19410 | 19420 | 19430 | 19440 |
| DZR12 | | | √ * | | |
| DZR10 | | | √ * | V * | |
| CZR15 | | | √ * | | |
| CZR12 | | | √ * | | |
| CZR10 | | | √ * | √ * | |
| DXR12mkII | | | √ * | | |
| DXR10mkII | | | √ * | √ * | |
| DXR8mkII | | | √ * | V * | |
| DHR12 | | | √ * | √ * | |
| DHR10 | | | √ * | √ * | |
| CHR12 | | | √ * | √ * | |
| CHR10 | | | √ * | V * | |
| DBR15 | | | V | | |
| DBR12 | | | V | V | |
| DBR10 | | | V | V | |
| CBR15 | | | V | | |
| CBR12 | | | V | V | |
| CBR10 | | | V | V | |
| HS8I | | | V | \checkmark | |
| HS7I | | | V | V | |
| HS5I | | | | | V |
| VXS5 | | | | | V |
| MSP3A | V | √ | | | V |
| MS101-4 | V | V | | | V |
| STAGEPAS600BT(mixer) | √ | | | | |
| STAGEPAS400BT (mixer) | V | | | | |
| MG10(X/XU/XUF) (mixer) | V | | | | |
| MG06(X) (mixer) | V | | | | |
| AG03MK2/06MK2 (mixer) | V | | | | |

* with U-Bracket